

HOW TO PROGRAMME A GUARDIAN OL6.5 SECTIONAL DOOR OPENER



① ⑥ ⑤ ③ ⑦



⑧



To set up the OL6.5 sectional door opener

- Have the door in the down position
- Press and release the **white LIMIT button**^①
- **Green LED**^② will light up
- Press and hold the **green UP button**^③ till door reaches top limit position
- Press and release the **white LIMIT button**^① to save
- Press and release the **white LIMIT button**^① twice
- **Red LED**^④ will light up
- Press and hold the **red DOWN button**^⑤ till door reaches bottom limit position
- Press and release the **white LIMIT button**^① to save
- Press and release the **blue FORCE button**^⑥
- Garage door will automatically travel to top limit, pause, then travel to bottom limit.
- Unit will beep 3 times and setup is complete.

To code handsets and wall button

- Press and release the **yellow RADIO SET button**^⑦
- The opener will beep once
- Press and release the **desired button**^⑧ on your handset or wall button you wish to code
- The opener will beep twice
- That button is now coded
- Repeat for any further button or wall button you wish to code